



PISO-P8R8U

Universal PCI, 8-ch Optically Isolated Digital Input and 8 Relay Output Board

Introduction

The PISO-P8R8U Universal PCI card supports the 3.3 V/5 V PCI bus, and offers 8 optically-isolated Digital Input channels and 8 electromechanical Relay Output channels. The DI channels provide 5000 Vrms isolation protection that allows the input signals to be completely floated so as to prevent ground loops and isolate the host computer from potentially damaging voltage spikes. The Relay Output channels are used where it is necessary to control a circuit using a low-power signal, with complete electrical isolation between the control and the controlled circuits, or where several circuits must be controlled by a single signal.

The PISO-P8R8U can be used in a variety of applications, such as controlling the ON/OFF state of external devices, driving external relays or small power switches, activating alarms, contact closure, or sensing external voltages or switches, etc.

The PISO-P8R8U cards also include an onboard Card ID switch that enables the board to be recognized via software if two or more PISO-P8R8U cards are installed in the same computer. The PISO-P8R8U is designed as a direct replacement for the PISO-P8R8 without requiring any modification to the software or the driver.

Pin Assignments

Pin Assignment	Terminal No.	Pin Assignment
NO_0	01	
COM_0	02	
N/A	03	
NO_1	04	
COM_1	05	
N/A	06	
NO_2	07	
COM_2	08	
N/A	09	
NO_7	10	
COM_7	11	
DIA_0	12	
DIA_1	13	
DIA_2	14	
DIA_3	15	
DIA_4	16	
DIA_5	17	
DIA_6	18	
DIA_7	19	
	20	NO_3
	21	COM_3
	22	N/A
	23	NO_4
	24	COM_4
	25	NO_5
	26	COM_5
	27	NO_6
	28	COM_6
	29	N/A
	30	DIB_0
	31	DIB_1
	32	DIB_2
	33	DIB_3
	34	DIB_4
	35	DIB_5
	36	DIB_6
	37	DIB_7

CON1

Features

- Universal PCI (3.3 V/5 V) Interface
- Supports Card ID (SMD Switch)
- 8-channel Electromechanical Relay Output
- 8-channel Optically-isolated Digital Input
- AC Signal Input with Filter
- Selectable DC Signal Input Filter
- 5000 Vrms Photo-isolation Protection
- Onboard Relay Output Status LED Indicators



Software

Drivers

- 32/64-bit Windows XP/2003/2008/7/8/10
- Linux

Sample Programs

- DOS Lib and TC/BC/MSC Demo
- LabVIEW Toolkit
- VB/VC/Delphi/BCB/MATLAB Demo
- VB.NET/C#.NET/VC.NET Demo

Hardware Specifications

Hardware	
Card ID	Yes (4-bit)
Connector	Female DB37 x 1
Digital Input	
Channels	8
Type	Photocoupler (Sink and Source)
Response Speed	Without Filter: 50 kHz (Typical) With Filter: 0.455 kHz(Typical)
Trigger Mode	Static Update
Wet Contact, ON Voltage Level	AC/DC 5 ~ 24 V (AC 50 ~ 1 kHz)
Wet Contact, OFF Voltage Level	AC/DC 0 ~ 1 V
Isolation	5000 Vrms
Relay Output	
Channels	8
Type	SPST N.O.(Form A)
Contact Rating	AC: 250 V @ 1.6 A DC: 30 V @ 5 A
Operate Time	6 ms (Typical)
Release Time	3 ms (Typical)
Electrical Endurance	100,000 ops.
Mechanical Endurance	2,000,000 ops.
PC Bus	
Type	3.3 V/5 V Universal PCI, 32-bit, 33 MHz
Data Bus	8-bit
Power	
Consumption	300 mA @ +5 V
Mechanical	
Dimensions (mm)	105 x 149 x 22 (W x L x D)
Environmental	
Operating Temperature	0 ~ +60°C
Storage Temperature	-20 ~ +70°C
Humidity	5 ~ 85% RH, Non-condensing

Ordering Information

PCI-P8R8U CR	Universal PCI, 8-ch Optically Isolated Digital Input and 8 Relay Output Board (RoHS) Includes one CA-4002 D-Sub connector.
---------------------	--

Accessories

	CA-3710	DB-37 Male-Male D-sub cable 1 M (Cable for Daughter Board (45°))
	CA-3710D	DB-37 Male-Male D-sub cable 1 M (Cable for Daughter Board (180°))
	CA-3715DM-H	DB-37 Male-Male Cable, 1.5 M, 180°. (RoHS)
	CA-3730DM-H	DB-37 Male-Male Cable, 3.0 M, 180°. (RoHS)
	CA-3750DM	DB-37 Male-Male Cable, 5.0 M, 180°. (RoHS)
	CA-3750DM-H	DB-37 Male-Male Cable, 5.0 M, 180°. (RoHS)
	CA-4002	37-pin Male D-sub connector with plastic cover.
	DB-37	Directly connect signal to D-sub 37-pin connector
	DN-37	DIN Rail Mounting 37-pin Connector

