



PCI-822LU

Universal PCI, 250 kS/s, 32-ch, 12-bit Analog Input
Multifunction Board (8 K WORD FIFO)

PCI-826LU

Universal PCI, 250 kS/s, 32-ch, 16-bit Analog Input
Multifunction Board (8 K WORD FIFO)

Introduction

The PCI-822LU/826LU is a series of multifunction boards that provides high-speed Analog and Digital I/O functions, and features a continuous 250 kS/s, 12- or 16-bit resolution AD converter, an 8-kSample hardware FIFO, a 2-channel, 16-bit DA converter, and 32 programmable Digital I/O channels with DO readback. The PCI-822LU/826LU series provides either 32 single-ended or 16 differential Analog Input channels that are jumper selectable, and is equipped with a high-speed PGA featuring programmable gain (1, 2, 4 or 8).

The PCI-822LU/826LU series also includes an onboard Card ID switch that enables the board to be easily recognized via software if two or more boards are installed in the same computer. The pull-high/low jumpers allow the DI status to be predefined instead of remaining floating if the DI channels are disconnected or interrupted.

The PCI-822LU/826LU series includes an AD channel scan function called MagicScan, which eliminates the majority of the effort required to acquire AD values, such as selecting the channel, setting the gain values and the settling time, triggering the ADC, and acquiring the data. Using the built-in MagicScan and the interrupt features, these complex tasks are effectively offloaded from the CPU. Even in MagicScan mode, a different gain code can be used for each channel, and the sampling rate can still reach a total of 250 kS/s, making the PCI-822LU/826LU series especially suitable for high-end applications.

Pin Assignments

Pin Assignment	Terminal No.	Pin Assignment	Pin Assignment	Terminal No.	Pin Assignment
AI_0	01	AI_16	PB 0	01	PB 1
AI_1	02	AI_17	PB 2	03	PB 3
AI_2	03	AI_18	PB 4	05	PB 5
AI_3	04	AI_19	PB 6	07	PB 7
AI_4	05	AI_20	PB 8	09	PB 9
AI_5	06	AI_21	PB 10	11	PB 11
AI_6	07	AI_22	PB 12	13	PB 13
AI_7	08	AI_23	PB 14	15	PB 15
AI_8	09	AI_24	GND	17	GND
AI_9	10	AI_25	+5 V	19	+12 V
AI_10	11	AI_26	CON1		
AI_11	12	AI_27	PA 0	01	PA 1
AI_12	13	AI_28	PA 2	03	PA 3
AI_13	14	AI_29	PA 4	05	PA 5
AI_14	15	AI_30	PA 6	07	PA 7
AI_15	16	AI_31	PA 8	09	PA 9
A.GND	17	Da2 out	PA 10	10	PA 11
Da1 out	18	D.GND	PA 12	12	PA 13
Ext_Trg	19		PA 14	14	PA 15
			GND	16	GND
			+5 V	18	+12 V
			CON2		

Features

- Universal PCI (3.3 V/5 V) Interface
- Supports Card ID (SMD Switch)
- 32 Single-ended/16 Differential Analog Input Channels
 - 12-bit 250 kS/s High-speed AD for PCI-822LU
 - 16-bit 250 kS/s High-speed AD for PCI-826LU
 - Built-in MagicScan Controller
 - Supports Software-trigger and Pacer-trigger
 - 8 K-sample Hardware FIFO
- 2-channel, 16-bit Analog Output
- 32-channel programmable DI/O
 - Pull-high and Pull-low Resistors for DI Channels
 - Supports Digital Output Status Readback (Register Level)



Software

Drivers

- 32/64-bit Windows XP/2003/2008/7/8/10 Linux

Sample Programs

- DOS Lib and TC/BC/MSC Demo LabVIEW Toolkit
- VB/VC/Delphi/BCB/VB.NET/C#.NET/VC.NET/MATLAB Demo
















Hardware Specifications

Model	PCI-822LU	PCI-826LU
Analog Input		
Channels	32 Single-ended/16 Differential	
Resolution	12-bit	16-bit
Sampling Rate	250 kS/s Max.	
FIFO Size	8192 Samples	
Accuracy	0.1% of FSR ± 1 LSB @ 25°C, ± 10 V	
Analog Output		
Channels	2	
Resolution	16-bit	
Accuracy	± 6 LSB	
Output Driving	± 5 mA	
Output Range	± 5 V, ± 10 V, $0 \sim +10$ V, $0 \sim +5$ V	
Slew Rate	0.7 V/ μ s	
Programmable Digital I/O		
Channels	32	
Compatibility	5 V/TTL	
Output Capability	Sink: 2.4 mA @ 0.8 V; Source: 0.8 mA @ 2.0 V	
General		
Bus Type	3.3 V/5 V Universal PCI, 32-bit, 33 MHz	
Card ID	Yes (4-bit)	
Connectors	Female DB37 x 1, 20-pin Box Header x 2	
Power Consumption	800 mA @ +5 V	
Operating Temperature	0°C to +60°C	
Humidity	5 to 85% RH, Non-condensing	

Ordering Information

PCI-822LU CR	Universal PCI, 250 kS/s, 32-ch, 12-bit Analog Input Multifunction Board (8 K WORD FIFO) (8 K WORD FIFO) (RoHS) Includes one CA-4002 D-Sub connector
PCI-826LU CR	Universal PCI, 250 kS/s, 32-ch, 16-bit Analog Input Multifunction Board (8 K WORD FIFO) (8 K WORD FIFO) (RoHS) Includes one CA-4002 D-Sub connector

Accessories

 ADP-20/PCI	Extender, Extended dual 20-pin flat-cable connector to PC slot window
 CA-2002	20-pin flat cable, 20 cm x 2
 CA-2010	20-pin flat cable, 1 M
 CA-2020	20-pin flat cable, 2 M.
 CA-3710	DB-37 Male-Male D-sub cable 1 M (Cable for Daughter Board (45°))
 CA-3710D	DB-37 Male-Male D-sub cable 1 M (Cable for Daughter Board (180°))
 CA-3715DM-H	DB-37 Male-Male Cable, 1.5 M, 180°. (RoHS)
 CA-3730DM-H	DB-37 Male-Male Cable, 3.0 M, 180°. (RoHS)
 CA-4002	37-pin Male D-sub connector with plastic cover.
 DB-1825	Analog Input Screw terminal Board
 DB-16P	16-channel Isolated Digital Input Daughter Board
 DB-16R	16-channel Relay Output Daughter Board
 DN-20/DN-20-381	20-pin DIN-RAIL mounting I/O connector board
 DN-37	DIN Rail Mounting 37-pin Connector
 125Ω, 0.1% DIP Resistors	125 Ω External Resistor for use with Current Input

